

# M01-MPS-NO/C


# M01-MPSE-NO/C



## Electronic Power Supply & Keypad

### MP-MPS-NO/C

Electronic Power Supply  
電子變壓器



#### SPECIFICATIONS :


Dimension : 175L x 80W x 65Dmm  
Input voltage : 220VAC, 50HZ  
Output voltage : 12VDC, 3A  
Time : 0~30sec.  
Built-in fuse for overload and short circuit protection

#### 規格:

外觀尺寸: 175L x 80W x 65Dmm  
輸入電壓: 220VAC, 50HZ  
輸出功率: 直流輸出標準12VDC、3A  
延時功能: 0-30秒  
內置保險管過載及短路保護

### MP-MPSE-NO/C

Electronic Power Supply  
電子變壓器



#### SPECIFICATIONS :

Dimension : 145L x 100W x 65Dmm  
Input voltage : 220VAC, 50HZ  
Output voltage : 12VDC, 3A  
Time : 0~30sec.  
Built-in fuse for overload and short circuit protection  
Exposed contact points for easy installation

#### 規格:

外觀尺寸: 145(L) x 100(W) x 65(H)  
輸入電壓: 220VAC, 50HZ  
輸出功率: 直流輸出標準12VDC、3A  
延時功能: 0-30秒  
內置保險管過載及短路保護  
外露接口方便施工

## MANILA CAPITCO CORPORATION

UNIT 6B, 2ND FLOOR DOLMAR BUILDING, U.N. AVENUE, PACO MANILA

PHONE NOS.: 02.533.3072 / 353.6302

FAX NOS.: 02.353.6301